

BDW 73 A	Si-N-Darl+Di	=BDW 73: 60V	17j	BD 901	17j
BDW 73 B	Si-N-Darl+Di	=BDW 73: 80V	17j	BD 901	17j
BDW 73 C	Si-N-Darl+Di	=BDW 73: 100V	17j	BD 901	17j
BDW 73 D	Si-N-Darl+Di	=BDW 73: 120V	17j	-	
BDW 74	Si-P-Darl+Di	NF-L, 45V, 8A, 80W, >1MHz, B>750	17j	BD 902	17j
BDW 74 A	Si-P-Darl+Di	=BDW 74: 60V	17j	BD 902	17j
BDW 74 B	Si-P-Darl+Di	=BDW 74: 80V	17j	BD 902	17j
BDW 74 C	Si-P-Darl+Di	=BDW 74: 100V	17j	BD 902	17j
BDW 74 D	Si-P-Darl+Di	=BDW 74: 120V	17j	-	
BDW 83	Si-N-Darl+Di	NF-L, 45V, 15A, 150W, >1MHz, B>750	18j	BDW 83 C	18j
BDW 83 A	Si-N-Darl+Di	=BDW 83: 60V	18j	BDW 83 C	18j
BDW 83 B	Si-N-Darl+Di	=BDW 83: 80V	18j	BDW 83 C	18j
BDW 83 C	Si-N-Darl+Di	=BDW 83: 100V	18j	BDW 83 C	18j
BDW 83 D	Si-N-Darl+Di	=BDW 83: 120V	18j	-	
BDW 84	Si-P-Darl+Di	NF-L, 45V, 15A, 150W, >1MHz, B>750	18j	BDW 84 C	18j
BDW 84 A	Si-P-Darl+Di	=BDW 84: 60V	18j	BDW 84 C	18j
BDW 84 B	Si-P-Darl+Di	=BDW 84: 80V	18j	BDW 84 C	18j
BDW 84 C	Si-P-Darl+Di	=BDW 84: 100V	18j	BDW 84 C	18j
BDW 84 D	Si-P-Darl+Di	=BDW 84: 120V	18j	-	
BDW 91	Si-N-Darl+Di	NF/S, 180V, 4A, 10W(Tc=25°), 20MHz	2a	-	
BDW 92	Si-P-Darl+Di	NF/S, 180V, 4A, 10W(Tc=25°), 20MHz	2a	-	
BDW 93	Si-N-Darl+Di	NF-L, 45V, 12A, 80W, >20MHz, B>750	17j	BDW 93 C	17j
BDW 93 A	Si-N-Darl+Di	=BDW 93: 60V	17j	BDW 93 C	17j
BDW 93 B	Si-N-Darl+Di	=BDW 93: 80V	17j	BDW 93 C	17j
BDW 93 C	Si-N-Darl+Di	=BDW 93: 100V	17j	BDW 93 C	17j
BDW 93 CFI	Si-N-Darl+Di	=BDW 93C: Iso, 40W	17c	(BDW 93C)	17j
BDW 94	Si-P-Darl+Di	NF-L, 45V, 12A, 80W, >20MHz, B>750	17j	BDW 94 C	17j
BDW 94 A	Si-P-Darl+Di	=BDW 94: 60V	17j	BDW 94 C	17j
BDW 94 B	Si-P-Darl+Di	=BDW 94: 80V	17j	BDW 94 C	17j
BDW 94 C	Si-P-Darl+Di	=BDW 94: 100V	17j	BDW 94 C	17j
BDW 94 CFI	Si-P-Darl+Di	=BDW 94C: Iso, 40W	17c	(BDW 94C)	17j

BDX

BDX 10(C,H)	Si-N	NF/S-L, 100V, 15A, 117W, >0,8MHz	23a	2N3055	23a
BDX 11	Si-N	NF/S-L, 160V, 10A, 117W, >0,8MHz	23a	2SD1047	18j
BDX 12	Si-N	NF/S-L, 140V, 10A, 100W, >0,8MHz	23a	2SD1047	18j
BDX 13	Si-N	NF/S-L, 50V, 15A, 117W, >0,8MHz	23a	BD 317	23a
BDX 14	Si-P	NF/S-L, 90V, 4A, 29W, >4MHz	22a	BD 244 C	17j
BDX 15	Si-P	NF/S-L, -70V, 10A, 117W, >0,8MHz	23a	BD 318	23a
BDX 16	Si-P	NF/S-L, 160V, 3A, 25W, 4MHz	22a	(2SB861)	17j
BDX 18	Si-P	NF/S-L, 100V, 15A, 117W, 4MHz	23a	BD 318	23a
BDX 18 N	Si-P	=BDX 18: 70V	23a	BD 318	23a
BDX 20	Si-P	NF/S-L, 160V, 10A, 117W, >4MHz	23a	2SB817	18j
BDX 22	Si-N	NF/S-L, 160V, 10A, 37,5W, >0,8MHz	22a	-	
BDX 23	Si-N	NF/S-L, 95V, 15A, 117W, >0,8MHz	23a	BD 317	23a
BDX 24	Si-N	NF/S-L, 50V, 4A, 29W, >0,8MHz	22a	BD 243 C	17j
BDX 25	Si-N	NF/S-L, 130V, 5A, 34W(Tc=45°), 30MHz	22a	(BU 406)	17j
BDX 26	Si-P	NF/S-L, 40V, 5A, 40W, >30MHz	23a	BD 246 C	18j
BDX 27	Si-P	NF/S-L, 40V, 5A, 50W(Tc=45°), 50MHz	22a	BD 244 C	17j
BDX 28	Si-P	=BDX 27: 60V	22a	BD 244 C	17j
BDX 29	Si-P	=BDX 27: 80V	22a	BD 244 C	17j
BDX 30	Si-P	=BDX 27: 125V	22a	(BD 244 C)	17j
BDX 31	Si-N	TV-HA, 2200V, 4A, 40W	23a	-	**
BDX 32	Si-N	=BDX 31: 1700V	23a	2SC3026	23a
BDX 33	Si-N-Darl+Di	NF-L, 45V, 10A, 70W, >20MHz, B>750	17j	BDW 93 C	17j